

A

THE COMMISSIONER OF PATENTS AND TRADEMARKS
WASHINGTON, D.C. 20231

Case Docket No.: 1068/5

66/03/99
JC594
U.S. PTO
09/324515

JC594 U.S. PTO
09/324515
06/03/99

Enclosed herewith for filing is the patent application of
DOTAN SOKOLOV AND DAVID BEN-ELI
For CELLULAR TELEPHONY SEARCHER

Enclosed are:

- ☒ 3 sheets of informal drawing(s).
- ☒ An assignment of the invention to DR. MARK FRIEDMAN LTD
- ☐ A certified copy of a _____ application.
- ☐ An associate power of attorney.
- ☐ A verified statement to establish small entity status under 37 CFR 1.9 and 37 CFR 1.27.
- ☐ Other - _____

The filing fee has been calculated as shown below:

(Col.1)	(Col.2)	
FOR:	NO. FILED	NO. EXTRA
BASIC FEE		
TOTAL CLAIMS	23 - 20 =	
INDEP CLAIMS	- 3 =	
... Record of Assignment		40

SMALL ENTITY	
RATE	FEE
	\$ 380
x9 =	\$
x39	\$
	\$
TOTAL	\$

OTHER THAN A SMALL ENTITY	
RATE	FEE
	\$ 760
3 x 18 =	\$ 54
x78	\$
	\$ 40
TOTAL	\$ 854

* If the difference in Col.1 is less than zero, enter "0" in Col.2

- ☒ Please charge my Deposit Account No. 06-2140 in the amount of \$ 854. A duplicate copy of this sheet is enclosed.
- ☐ A check in the amount of \$_____ to cover the filing fee is enclosed.
- ☒ The Commissioner is hereby authorized to charge payment of the following fees associated with this communication or credit any overpayment to Deposit Account No. 06-2140. A duplicate copy of this sheet is enclosed.
 - ☒ Any additional filing fees required under 37 CFR 1.16.
 - ☒ Any patent application processing fees under 37 CFR 1.17.
- ☒ The Commissioner is hereby authorized to charge payment of the following fees during the pendency of this application or credit any overpayment to Deposit Account No. 06-2140. A duplicate copy of this sheet is enclosed.
 - ☒ Any patent application processing fees under 37 CFR 1.17.
 - ☐ The issue fee set in 37 CFR 1.18 at or before mailing of the Notice of allowance, pursuant to 37 CFR 1.311(b).
 - ☒ Any filing fees under 37 CFR 1.16 for presentation of extra claims.

Respectfully,

Mark M. Friedman
Reg. No. 33,883

Mark M. Friedman
DR. MARK FRIEDMAN LTD.
C/O Anthony Castorina
2001 Jefferson Davis Highway
Suite 207
Arlington, Virginia 22202

APPLICATION FOR PATENT

Inventors: Dotan Sokolov and David Ben-Eli

Title: CELLULAR TELEPHONY SEARCHER

FIELD AND BACKGROUND OF THE INVENTION

The present invention relates to cellular telephony and, more particularly, to a searcher for a DSSS cellular telephony system.

In a DSSS cellular telephony system, the base stations identify themselves by transmitting pilot signals. Each pilot signal is a sequence of zero bits, modulated, according to the principles of DSSS encoding, by a pseudonoise (PN) sequence, or an extended pseudonoise sequence.

For example, under the IS-95 interim standard, the PN sequence is 2^{15} chips long, with the n -th chip including an in-phase component $i(n)$ and a quadrature component $q(n)$. The initial values of i and q are $i(1)=q(1)=1$ and $i(n)=q(n)=0$ for $2 \leq n \leq 15$. Subsequent values of i and q , up to $n=2^{15}-1$, are obtained recursively as follows:

$$i(n) = i(n-15) + i(n-10) + i(n-8) + i(n-7) + i(n-6) + i(n-2) \quad (1)$$

$$q(n) = q(n-15) + q(n-12) + q(n-11) + q(n-10) + q(n-9) + q(n-5) + q(n-4) + q(n-3) \quad (2)$$

where the additions are modulo 2. Finally, $i(2^{15})=q(2^{15})=0$.

The same PN sequence is used by each of the base stations. The base stations are synchronized; and each base station uses the PN sequence with a different delay (also called "PN offset") to produce the pilot signal. This enables the mobile units of the cellular telephony network to distinguish one base station from another.

The total signal received by a mobile station, as a function of time t , is:

$$RX(t) = \sum_{b=1}^B \sum_{m=1}^{M_b} C(b, m, t) \cdot PN(t + \text{offset}(b) + \tau(b, m)) \cdot \left[1 + \sum_{i=1}^{I_b} \alpha_i \cdot D(i, b, t) \cdot W(i, b) \right] + N \quad (3)$$

Here, b indexes the B base stations; m indexes the M_b transmission paths (multipath channels) from base station b to the mobile station; C is the channel gain of multipath channel m ; τ is the additional delay introduced to the PN sequence by multipath channel m ; the “1” inside the brackets represents the sequence of zeros that is modulated by the base stations to produce the pilot signals; i indexes the I_b other users that are transmitting via base station b at time t ; α is the power of user i relative to the pilot signal; D is the data transmitted by user i ; W is a code sequence (for example, a Hadamard code sequence) that is used in addition to the PN sequence to modulate data D and allow simultaneous transmission on the same physical channel by all the users in addition to the pilot signals; and N is additive noise.

Each mobile unit of the cellular telephony network determines which base station to communicate with (typically, the nearest base station) by correlating this signal with the PN sequence at a set of trial delays. Because data D are modulated by sequences W , the correlation of the part of the signal that comes from other users is negligible. The correlation with the pilot signals also is negligible, except at trial delays that are equal to the PN offsets used by the base stations, as modified by multipath delays τ . Specifically, a pilot signal that arrives at a delay, that is equal to the sum of a base station offset and one of the multipath delays τ associated with transmissions from that base station, gives a significant contribution to the correlation at a matching trial delay; and all other pilot signals contribute negligibly to the

correlation at that trial delay. This correlating is performed when the mobile station powers up, and continuously thereafter, to allow handover from one base station to another when the mobile station crosses a cell boundary. The delays of the various base stations are well separated, by more than the largest anticipated multipath delay, so in the absence of additive noise and in the absence of multipath delays, only a small number of correlations, equal to the number of potential nearest base stations, would have to be performed, to identify the base station whose delay gives the highest correlation as the nearest base station. . According to the IS-95 standard, this separation is at least 256 chip durations T_C . Because the pilot signals and data D are received by the mobile station from each base station via several paths at different delays (PN offset + τ), the various replicas of the signals thus received are combined to suppress the deterministic noise represented by the various multipath delays τ . For example, maximal ratio combining is the optimal combination method in a bit error rate and frame error rate sense. In order to do this combining, the multipath delays must be determined. Therefore, the correlation is performed at a series of delays in a window centered on the nominal delay. The size of this window depends on the local topography, and is provided to the mobile unit by the base station. One typical window size, according to the IS-95 standard, is 60 chip durations.

Figure 3 is a schematic block diagram of a mobile station receiver 30. RF signals are received by an antenna 60, downconverted to an intermediate frequency (IF) by a downconverter 62, filtered by a bandpass filter 64 (typically a surface acoustic wave filter) to eliminate signals outside the required bandwidth, and amplified by an automatic gain control 66. The amplified IF signals are multiplied by an IF sinusoid 65, without (block 68i) and with (block 68q) a 90° phase shift 67, to

produce an in-phase signal **I** and a quadrature signal **Q**. In-phase signal **I** is filtered by a low-pass filter **70i** and digitized by an A/D converter **72i**. Similarly, quadrature signal **Q** is filtered by a low-pass filter **70q** and digitized by an A/D converter **72q**. A searcher **80** receives the digitized signals and performs the correlations needed to determine the various multipath delays τ inside the target window. The digitized signals are again correlated, at the delays determined by searcher **80**, by the correlators of a correlator bank **74**, and the outputs of correlator bank **74** are combined, in a maximal ratio sense, in a rake combiner **76** to produce the final output signal.

10 In order to ensure uninterrupted communication as a mobile station crosses from one cell to another, the correlations performed by searcher **80** must be performed rapidly. In fact, it is not necessary to perform the full correlation at each delay in the window. It suffices to perform a correlation that is only long enough to ensure a high detection probability at the right delay and a low false alarm probability at the wrong delay. Typically, the length of the correlation, measured as a multiple N of the chip duration T_c , is between $500T_c$ and $2000T_c$.

To make the correlations even more efficient, the dual dwell algorithm is used. At each delay in the window, the correlation is performed for a number M of chip durations that is less than N . Only if the correlation value after M chip durations exceeds a certain threshold is the correlation performed for the full N chip durations. The threshold, and the parameters N and M , are chosen to maximize the detection probability while minimizing both the false alarm probability and the time spent correlating. See, for example, M. K. Simon, J. K. Omura, R. A. Scholtz and B. K. Levitt, *Spread Spectrum Communication, Vol. III*, Computer Science Press, 1989,

chapter 1, particularly section 1.3, and D. M. Dicarlo and C. L. Weber, "Multiple dwell serial search: performance and application to direct sequence code acquisition", *IEEE Transactions on Communications* vol. COM-31 no. 5 pp. 650-659, May 1983.

In the prior art implementation of this algorithm, several correlators are used by
 5 searcher **80** to correlate the received pilot signal with the PN sequence at several adjacent delays in the window. If none of the correlation values exceeds the threshold after M chip durations, then the correlators are used to correlate the received pilot signal with the PN sequence at the next several adjacent delays. If at least one of the correlation values exceeds the threshold after M chip durations, then all the
 10 correlations are continued for the full N chip durations, but only the correlation values obtained by the correlators whose correlation values exceeded the threshold after the initial M chip durations are actually considered. The brute force approach to reducing search time, adding more correlators, is inefficient, because the more correlators that are used, the more likely it is that one of the correlators passes the threshold. In that
 15 case, the other correlators, which did not pass the threshold, continue to correlate unnecessarily for the full N chip durations.

There is thus a widely recognized need for, and it would be highly advantageous to have, a configuration for a cellular telephony searcher that would allow the efficient use of many correlators.

20

SUMMARY OF THE INVENTION

According to the present invention there is provided a cellular telephony searcher, comprising: (a) a plurality of correlators for correlating a received signal with a pseudonoise sequence; (b) an input mechanism for inputting the pseudonoise

sequence into the correlators, each of the correlators receiving the pseudonoise sequence with a different delay; and (c) a delay management mechanism for initializing the delays and subsequently changing the delays, the changing being contingent, for each correlator, only on an output of the correlator.

5 According to the present invention there is provided, in a cellular telephony network including at least one base station and at least one mobile station, each of the at least one mobile station receiving a received signal from the at least one base station, the received signal including a plurality of received values, each received value having a real part and an imaginary part, a method for each of the at least one

10 mobile station to identify at least one multipath channel to use to communicate with one of the at least one base station, including the steps of: (a) generating a pseudonoise sequence; (b) simultaneously performing a plurality of initial correlations of the received signal with the pseudonoise sequence, each of the initial correlations being performed with a different initial delay of the pseudonoise sequence, the initial

15 correlations being performed for a first dwell time to produce, for each of the initial correlations, an initial first dwell time correlation value; and (c) for each initial correlation: (i) if an estimated absolute value of the initial first dwell time correlation value exceeds a threshold, continuing to perform the each initial correlation, (ii) otherwise, performing a first subsequent correlation of the received signal with the

20 pseudonoise sequence at a first subsequent delay different from any of the initial delays; wherein, if the performing of at least one of the initial correlations is continued and if at least one of the first subsequent correlations is performed, the continued performing of the at least one initial correlation and the performing of the at least one first subsequent correlation are effected simultaneously.

Although the examples presented herein are of a cellular telephony system according to the IS-95 standard, it is to be understood that the principles of the present invention apply to any DSSS cellular telephony system. In addition, although the examples presented herein are directed at an implementation of a dual dwell
 5 algorithm, it will be clear to those skilled in the art how to apply the present invention to the implementation of a multiple dwell algorithm.

In the most general form of the present invention, the correlators correlate the received signal with the pseudonoise sequence at different trial delays, as initialized and changed periodically by the delay management mechanism. A correlator that
 10 succeeds in producing an output of sufficiently high absolute value is kept at its trial delay; a correlator that fails to produce an output of sufficiently high absolute value is moved to a different trial delay. The amount by which trial delays are changed depends on the outputs of all the correlators collectively; but the decision whether to change the trial delay of a specific correlator depends only on the output of that
 15 correlator, independent of the outputs of the other correlators. It is in this sense that the changing of a trial delay of a correlator is contingent only on the output of that correlator. This distinguishes the present invention from the prior art, in which all correlators are moved to new delays, or are not moved to new delays, in lock step.

More specifically, in the application of the present invention to multiple dwell
 20 algorithms generally, and to a dual dwell algorithm in particular, according to the present invention, if a correlator produces, after M chip durations, a correlation value that is less than the threshold, that correlator is assigned to a new delay in the window, and the correlation is repeated at the new delay, using this correlator, for another M chip durations. In this way, all the correlators are kept busy almost all the time.

Because of the more efficient use of the correlators according to the present invention, as compared with the relatively inefficient use of the correlators according to the prior art implementation of the dual dwell algorithm, the tradeoff between speed and efficient hardware utilization under the present invention allows the use of eight or
 5 more correlators, with the consequent increase in throughput vs. the prior art implementation.

For efficient implementation, N is made an integral multiple of M , typically $4M$. The time MT_C is referred to herein as the “first dwell time”. The time $(N-M)T_C$ is referred to herein as the “second dwell time”.

10 To allow this dynamic reassignment of correlators, a device of the present invention feeds the PN sequence from a PN sequence generator into a delay line. The delay line feeds multiple copies of the PN sequence, each copy at a different delay relative to the PN generator, to a multiplexer. Each correlator is provided with an index register, wherein is stored an index representative of the delay to which that
 15 correlator is assigned at any given time. The multiplexer reads the value stored in the index register and forwards the corresponding copy of the PN sequence to the correlator associated with that index register.

Each correlator has its own memory, each memory with a certain number R of registers. Periodically, after $y \leq R$ first dwell times, *i.e.*, after yM chip durations, an
 20 interrupt is generated and correlator outputs are read by system software. Correlator outputs that have been accumulated for a full N chip durations are used subsequently by system software to identify the strongest multipath components of the signals received from the neighboring base stations.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention is herein described, by way of example only, with reference to the accompanying drawings, wherein:

FIG. 1 is a partial block diagram of a searcher of the present invention;

5 FIG. 2 is a flow chart for the decision of whether to move a correlator to a new delay;

FIG. 3 (prior art) is a schematic block diagram of the receiver of a cellular telephony mobile unit.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

The present invention is of a cellular telephony searcher which can be used by a mobile station to identify the several strongest multipath components of nearby base stations faster than presently known searchers.

15 The principles and operation of a cellular telephony searcher according to the present invention may be better understood with reference to the drawings and the accompanying description.

Referring now to the drawings, Figure 1 is a partial block diagram of a searcher **10** of the present invention. Searcher **10** includes a PN sequence generator **12**, a delay line **14** that in turn includes several complex delay units **16**, a multiplexer **18**, several correlators **20**, a hold unit **26** and a next location unit **28**. With each correlator **20** is associated an index register **22** and a memory **24**. Memory **24** includes several complex registers and several corresponding integer registers, as discussed below. For illustrational simplicity, only two correlators **20** are shown, and only six delay units **16** are shown in delay line **14**. In practice, the preferred number

of correlators **20** is at least 8. The preferred number of delay units **16** is discussed below.

Also shown in Figure 1 is a receiver **30** and a clock **32**.

Block **30** of Figure 1 represents prior art receiver **30** of Figure 3, except for
 5 searcher **80**; and, in fact, according to the present invention, searcher **10** substitutes directly for searcher **80** in receiver **30** of Figure 3. The calculation performed by each correlator **20** is

$$S_K(\nu, \gamma) = \sum_{k=1}^K RX_{k+\nu} PN_{k+\nu-\gamma}^* \quad (4)$$

where the RX_k are successive values of the received signal of equation (3), the PN_k
 10 are successive values of the PN sequence received by correlator **20** from PN sequence generator **12**, and the summation index k runs from 1 to an upper limit K . The received signal is not necessarily sampled at the same rate as the PN sequence. In the examples presented herein, new samples RX_k are provided to correlators **20** by A/D converters **72** at time intervals of $T_c/2$. The parameter ν represents the time at which
 15 the correlation performed by a particular correlator **20** starts. The parameter γ represents the delay at which the correlation is performed, relative to the time at which the correlation starts. The samples RX_k and PN_k are complex, and the asterisk represents complex conjugation: PN_k^* is the complex conjugate of PN_k . For example, in a searcher **10** with four correlators, the correlation performed initially by the first
 20 correlator **20** is:

$$S = RX(0)PN(0) + RX(T_c)PN(T_c) + RX(2T_c)PN(2T_c) + RX(3T_c)PN(3T_c) + \dots \quad (5)$$

the correlation performed initially by the second correlator **20** is:

$$\begin{aligned}
S = & RX(T_c/2)PN(0) + RX(3T_c/2)PN(T_c) + RX(5T_c/2)PN(2T_c) \\
& + RX(7T_c/2)PN(3T_c) + \dots
\end{aligned} \tag{6}$$

the correlation performed initially by the third correlator **20** is:

$$\begin{aligned}
S = & RX(T_c)PN(0) + RX(2T_c)PN(T_c) + RX(3T_c)PN(2T_c) \\
& + RX(4T_c)PN(3T_c) + \dots
\end{aligned} \tag{7}$$

and the correlation performed initially by the fourth correlator **20** is:

$$\begin{aligned}
S = & RX(3T_c/2)PN(0) + RX(5T_c/2)PN(T_c) + RX(7T_c/2)PN(2T_c) \\
& + RX(9T_c/2)PN(3T_c) + \dots
\end{aligned} \tag{8}$$

(In equations (5)-(8), RX and PN are shown as functions of time, rather than as sampled values.) Note that correlators **20** do not all start correlating at the same time. In this example, the first correlator **20** starts correlating at time $t=0$; the second correlator **20** starts correlating at time $t=T_c/2$; the third correlator **20** starts correlating at time $t=T_c$; and the fourth correlator **20** starts correlating at time $t=3T_c/2$. Note also that, in this example at least, each correlator **20** receives the PN sequence with a delay corresponding to the time at which that correlator **20** starts its calculation. After M chip durations T_c ($K=M$), $S_K=S_M$ is the first dwell correlation value. After N chip durations T_c ($K=N$), $S_K=S_N$ is the second dwell correlation value.

Similarly, clock **32** is not part of searcher **10**, but is the system clock of the mobile station of which searcher **10** is a high level component. Clock **32** drives PN sequence generator **12** under the control of hold unit **26**, as described below.

PN sequence generator **12** produces a new value PN_k every chip duration T_c . Each new term in the right hand side of equation (4) also is computed by each correlator **20** once every T_c . In any particular T_c interval, all correlators **20** receive from A/D converters **72** one of two different values RX_k but each correlator **20**

receives from PN sequence generator 12, via delay line 14 and multiplexer 18, a different value PN_k , depending on the value of an index stored in index register 22 associated with that correlator 20.

Conceptually, once every T_c interval, each correlator 20 performs the multiplication $RX_k PN_k^*$ and adds the complex product thus obtained to a correlation value stored in one of the complex registers in memory 24 associated with that correlator 20. Because the possible values of the PN_k samples are either +1 or -1, there is no need to actually perform multiplications. Instead, only additions or subtractions of the in-phase and quadrature components of RX_k are actually performed. This allows a significant reduction in the complexity and electrical current consumption of searcher 10.

For example, let $A = \text{Re}(RX_k) + \text{Im}(RX_k)$ and let $B = \text{Re}(RX_k) - \text{Im}(RX_k)$. If $\text{Re}(PN_k) = 1$ and $\text{Im}(PN_k) = 1$, then $\text{Re}(RX_k PN_k^*) = A$ and $\text{Im}(RX_k PN_k^*) = -B$. If $\text{Re}(PN_k) = 1$ and $\text{Im}(PN_k) = -1$, then $\text{Re}(RX_k PN_k^*) = B$ and $\text{Im}(RX_k PN_k^*) = A$. If $\text{Re}(PN_k) = -1$ and $\text{Im}(PN_k) = 1$, then $\text{Re}(RX_k PN_k^*) = -B$ and $\text{Im}(RX_k PN_k^*) = -A$. If $\text{Re}(PN_k) = -1$ and $\text{Im}(PN_k) = -1$, then $\text{Re}(RX_k PN_k^*) = -A$ and $\text{Im}(RX_k PN_k^*) = B$. Instead of transferring RX_k directly from receiver 30 to correlators 20, RX_k is sent to an arithmetic unit (not shown) that computes A and B and sends A and B to the appropriate correlators 20. Each correlator 20 then adds $\pm A$ or $\pm B$ to the real part and the imaginary part of the correlation value, depending on the signs of the values of $\text{Re}(PN_k)$ and $\text{Im}(PN_k)$ concurrently provided by multiplexer 18 to that correlator 20.

Another method of avoiding actual multiplications exploits the fact that only the absolute values of the correlation values S are actually needed, to further reduce the number of calculations and achieve a further reduction in electrical current

consumption by searcher 10. If the complex PN sequence of every correlator 20 is rotated 45° , then either the real part or the imaginary part of every PN_k sample is equal to zero. Each correlator 20 then adds either $\pm \text{Re}(RX_k)$ or $\pm \text{Im}(RX_k)$ to the real part or the imaginary part of S , depending on the sign of the non-zero component of PN_k , without the intervention of the arithmetic unit. The rotation as described implicitly divides the complex PN sequence by the square root of 2. If only the relative values of S are required, then the system software uses these values of S as produced by correlators 20. If the absolute values of S are needed, then the system software normalizes the values of S that it obtains from searcher 10 by multiplying those values by the square root of 2.

Each delay unit 16 receives the PN sequence, either directly from PN sequence generator 12 in the case of the first (leftmost) delay unit 16, or from the immediately preceding delay unit 16. Each delay unit passes the PN sequence, with a fixed delay D , to multiplexer 18 and (except for the last (rightmost) delay unit 16) to the next delay unit 16. PN sequence generator 12 also passes the PN sequence directly to multiplexer 18. Thus, if there are N_D delay units 16 in delay line 14, multiplexer 18 receives N_D+1 copies of the PN sequence, with mutual relative delays D . The size of D , and the sampling rate at which RX_k samples are provided to correlators 20, are selected to give searcher 10 the required time resolution. In the example of equations (5)-(8), in which the sampling rate of RX_k is $(T_c/2)^{-1}$, the time resolution of searcher 10 is $T_c/2$.

Searcher 10 functions under the overall control of the system software to search for the delays, in all the relevant windows, that give correlation values that are significantly meaningful (i.e., above background noise) to be useful in identifying the

strong neighboring base stations and in demodulating the signals received from these base stations. For each window, the search process is initialized by setting the delay of PN sequence generator **12** to the first (earliest) delay in the window, by setting the indices stored in index registers **22** to values corresponding to the first L delays in the window (L being the number of correlators **20**), and by zeroing the complex registers of memories **24**. Subsequently, hold unit **26** delays PN sequence generator **12** further, as described below. In all cases, hold unit **26** delays PN sequence generator **12** by blocking timing signals from clock **32**.

Whenever a correlator **20** finishes a correlation over M chip intervals, next location unit **28** decides whether that correlator **20** should continue correlating at its current delay or should move to the next delay. Figure 2 is a flow chart of this decision. If $K=M$ (block **40**), correlator **20** has finished the first dwell correlation, so the absolute value of $S_K=S_M$ is compared to the first dwell threshold (block **42**). If $|S_M|$ is less than or equal to the first dwell threshold, the correlation at the current delay has failed, so correlator **20** is moved to the next delay that needs to be tested (block **48**). If $|S_M|$ exceeds the first dwell threshold, then correlator **20** stays at the current delay (block **46**) and continues the summation of equation (4) until N terms $RX_kPN_k^*$ have been summed. If $K>M$ (block **40**), then, in the general case of $N>2M$, either correlator **20** is in the middle of computing the second dwell correlation value S_N ($K<N$) or correlator **20** has finished computing the second dwell correlation value ($K=N$) (block **44**). If correlator **20** is in the middle of computing S_N , then correlator **20** remains at the current delay (block **50**). Otherwise, correlator **20** is moved to the next delay that needs to be tested.

In the special case of $N=2M$, $K>M$ implies $K=N$, so the “no” branch of block 40 leads directly to block 48.

Most preferably, the exact absolute value of S_M is not compared to the threshold. Instead the following piecewise linear approximation of $|S_M|$, which is based on a linear approximation of $\sqrt{1+x^2}$, and which is easier to implement in hardware than an exact numerical calculation of the absolute value of S_M , is used for the absolute value of S_M :

$$|S_M| \approx \max(|\text{Re}(S_M)|, |\text{Im}(S_M)|) + \min(|\text{Re}(S_M)|, |\text{Im}(S_M)|)/4 \quad (9)$$

[Are you sure about the factor of 1/4? If $S = x + iy$, and $x > y$, then I get:

$$|S| = (x^2 + y^2)^{1/2} = |x|(1 + (y^2/x^2))^{1/2} \approx |x|(1 + (y/(2|x|)))^{1/2} = |x| + |y|/2]$$

This approximation is sufficiently accurate for first dwell thresholding, and allows the implementation of the first dwell threshold decision in a hardware unit that is smaller, and consumes less electrical current, than would otherwise be necessary. By contrast, the exact absolute value of S_N is computed, for trial delays that pass the first dwell threshold, in software, so that the various $|S_N|$'s can be compared to determine the delays with the largest $|S_N|$ s. The fact that only a small number of trial delays pass the first dwell threshold keeps the associated computational load on the system software relatively low, with no sacrifice in accuracy.

Recall that each memory 24 includes several complex registers for storing S_K . The register depth, *i.e.*, the number R of complex registers, depends on how often (multiple of MT_C) an interrupt is generated to allow the reading of the most recently calculated value of S and the reading of the index value in the associated integer register. For example, if the interrupt is generated every $2MT_C$, then R should be at least 2, and in general if the interrupt is generated every yMT_C (y being an integer)

then R should be at least as great as y . If $y < R$, then the R complex registers are activated cyclically, giving the system software more time to respond to interrupts. R and y are implementation-dependent parameters. There are several considerations in the selection of the optimum values of y and R . Values of y and R that are too small
 5 put too much of a burden on system software. Large values of y and R require a correspondingly long delay line and a larger chip area devoted to memories **24**. The preferred value of both R and y is 2. Most preferably, to minimize the burden on system software, an interrupt is issued to system software only when all correlators **20** have filled their respective memories **24**.

10 Next location unit **28** also includes a next location register. At the start of correlation in a given window, the value in the next location register is set to the index corresponding to the first delay after the initial L delays. Subsequently, whenever block **48** is reached for a given correlator **20**, the value stored in the next location register is:

- 15 (a) copied to index register **22** of that correlator **20** and then
 (b) changed to the index corresponding to the delay immediately following the delay to which that correlator **20** has now been set.

Every yM chip intervals, while the interrupt service routine reads the output of searcher **10**, the system software determines the delay of the locally generated PN
 20 sequence that is to be used now by each correlator **20**, and signals hold unit **26** to pause PN sequence generator **12** until the timing of the generation of the PN sequence by PN sequence generator **12** matches the earliest delay of the forthcoming M chip intervals. At the same time, multiplexer **18** shifts the input of the PN sequence to each correlator **20** correspondingly, to preserve the continuity of input to each

correlator 20. This allows the use of a delay line 14 that is much shorter than the window. Specifically, the minimum value of N_D , the number of delay units 16 in delay line 14, is $\frac{L}{2} \frac{N}{M} + \Delta$ where Δ is an implementation dependent parameter:

$\Delta = Ly/2$, where y is the interrupt interval factor defined above.

5 Preferably, the components illustrated in Figure 1 all are implemented in hardware. The details of such a hardware implementation will be obvious to those skilled in the art.

 The following is an example of the functioning of searcher 10, with $L=8$ correlators 20 and with $D=T_c/2$, $M=512$, $N=3M=1536$ and $y=2$. In this example, the value of the indices in index registers 22 and in the next location register of next location unit 28 are given as (possibly fractional) multiples of T_c . In practice, because index registers 22 are integer registers, the values actually stored in index registers 22 are appropriate integral multipliers of D . Similarly, the delays are expressed as multiples of T_c relative to the center of the window. A correlator 20 is said to “fail the first dwell threshold” if that correlator 20 produces a first dwell correlation value S_M less than or equal in absolute value to the first dwell threshold, and to “pass the first dwell threshold” if that correlator 20 produces a first dwell correlation value S_M having an absolute value greater than the first dwell threshold. All correlators 20 have two complex registers in memories 24 for accumulating correlation values.

20 Following the IS-95 standard, the first correlation is performed at a delay of -30.

Table 1: Status at Time = 0

correlator no.	status	new value	index	corresponding delay	new value in next location register
1		0		-30	
2		$1/2$		$-29\frac{1}{2}$	
3		1		-29	
4		$1\frac{1}{2}$		$-28\frac{1}{2}$	
5		2		-28	
6		$2\frac{1}{2}$		$-27\frac{1}{2}$	
7		3		-27	
8		$3\frac{1}{2}$		$-26\frac{1}{2}$	4

Table 2: Status at time = $512T_c$

correlator no.	status	new value	index	corresponding delay	new value in next location register
1	fail threshold	4		-26	$4\frac{1}{2}$
2	fail threshold	$4\frac{1}{2}$		$-25\frac{1}{2}$	5
3	fail threshold	5		-25	$5\frac{1}{2}$
4	fail threshold	$5\frac{1}{2}$		$-24\frac{1}{2}$	6
5	fail threshold	6		-24	$6\frac{1}{2}$
6	fail threshold	$6\frac{1}{2}$		$-23\frac{1}{2}$	7
7	fail threshold	7		-23	$7\frac{1}{2}$
8	fail threshold	$7\frac{1}{2}$		$-22\frac{1}{2}$	8

Note: All the correlators have failed the first dwell threshold. Therefore, all the index registers are incremented by 4.

Table 3: Status at time = $1024T_c$

correlator no.	status	new value	index	corresponding delay	new value in next location register
1	fail threshold	8		-22	$8\frac{1}{2}$
2	fail threshold	$8\frac{1}{2}$		$-21\frac{1}{2}$	9
3	pass threshold	5		-25	9
4	fail threshold	9		-21	$9\frac{1}{2}$
5	fail threshold	$9\frac{1}{2}$		$-20\frac{1}{2}$	10
6	pass threshold	$6\frac{1}{2}$		$-23\frac{1}{2}$	10
7	fail threshold	10		-20	$10\frac{1}{2}$
8	fail threshold	$10\frac{1}{2}$		$-19\frac{1}{2}$	11

Note: Correlators 3 and 6 have passed the first dwell threshold. Therefore, these two correlators remain at their old delays, to continue correlating for the second dwell time. The other correlators, having failed the first dwell threshold, are set to the next delays.

Now, an interrupt is generated. Hold unit **26** performs a hold of $5T_c$, which is the delay of the earliest correlator (correlator 3) relative to the start of the window, and 5 is subtracted from all the index values and from the value in the next location register.

Table 4: Status at time = $1536T_c$

correlator no.	status	new value	index	corresponding delay	new value in next location register
1	fail threshold	6		-19	$6\frac{1}{2}$
2	fail threshold	$6\frac{1}{2}$		$-18\frac{1}{2}$	7
3	continue (2 nd)	0		-25	7
4	fail threshold	7		-18	$7\frac{1}{2}$
5	fail threshold	$7\frac{1}{2}$		$-17\frac{1}{2}$	8
6	continue (2 nd)	$1\frac{1}{2}$		$-23\frac{1}{2}$	8
7	fail threshold	8		-17	$8\frac{1}{2}$
8	pass threshold	$5\frac{1}{2}$		$-19\frac{1}{2}$	$8\frac{1}{2}$

Note: Correlator 8, which has passed the first dwell threshold, and correlators 3 and 6, which are correlating in the second dwell time, are kept at their old delays. The other correlators are set to the next delays.

Table 5: Status at time = $2048T_c$

correlator no.	status	new value	index	corresponding delay	new value in next location register
1	fail threshold	$8\frac{1}{2}$		$-16\frac{1}{2}$	9
2	pass threshold	$6\frac{1}{2}$		$-18\frac{1}{2}$	9
3	continue (3 rd)	0		-25	9
4	fail threshold	9		-16	$9\frac{1}{2}$
5	fail threshold	$9\frac{1}{2}$		$-15\frac{1}{2}$	10
6	continue (3 rd)	$1\frac{1}{2}$		$-23\frac{1}{2}$	10
7	fail threshold	10		-15	$10\frac{1}{2}$
8	continue (2 nd)	$5\frac{1}{2}$		$-19\frac{1}{2}$	$10\frac{1}{2}$

Note: Correlator 2, which has passed the first dwell threshold, and correlators 3, 6 and 8, which are correlating in the second dwell time, are kept at their old delays. The other correlators are set to the next delays.

An interrupt is again generated, but no hold is performed because the earliest correlator still is correlator 3.

Table 6: Status at time = $2560T_c$

correlator no.	status	new index value	corresponding delay	new value in next location register
1	fail threshold	$10^{1/2}$	$-14^{1/2}$	11
2	continue (2 nd)	$6^{1/2}$	$-18^{1/2}$	11
3	finish (new location)	11	-14	$11^{1/2}$
4	fail threshold	$11^{1/2}$	$-13^{1/2}$	12
5	fail threshold	12	-13	$12^{1/2}$
6	finish (new location)	$12^{1/2}$	$-12^{1/2}$	13
7	fail threshold	13	-12	$13^{1/2}$
8	continue (3 rd)	$5^{1/2}$	$-19^{1/2}$	$10^{1/2}$

- 5 Note: Correlators 2 and 8, which are correlating in the second dwell time, remain at their old delays. The other correlators, which either have failed the first dwell threshold or have completed the full first and second dwell correlations, are set to the next delays. In correlators 3 and 6, the active memory registers now store S_N , the second dwell correlation value.

10

Table 7: Status at time = $3072T_c$

correlator no.	status	new index value	corresponding delay	new value in next location register
1	fail threshold	$13^{1/2}$	$-11^{1/2}$	14
2	continue (3 rd)	$6^{1/2}$	$-18^{1/2}$	11
3	fail threshold	14	-11	$14^{1/2}$
4	pass threshold	$11^{1/2}$	$-13^{1/2}$	$14^{1/2}$
5	fail threshold	$14^{1/2}$	$-10^{1/2}$	15
6	pass threshold	$12^{1/2}$	$-12^{1/2}$	15
7	fail threshold	15	-10	$15^{1/2}$
8	finish (new location)	$15^{1/2}$	$-9^{1/2}$	16

- An interrupt is again generated. S_N is read from the inactive complex registers of the memories of correlators 3 and 6. The corresponding indices are read from the corresponding integer registers of the memories of correlators 3 and 6. Hold unit
- 15 26

performs a hold of $6T_c$ because the earliest correlator (correlator 2) is advanced by $13T_c/2$ relative to PN sequence generator 12. Correspondingly, 6 is subtracted from all of the index values and from the value in the next location register.

The operations performed by searcher 10 are partitioned between hardware and software in a manner that makes optimal use of the relative strengths and weaknesses of hardware and software. Specifically, operations associated with high current consumption are implemented in hardware, and numerically intensive operations are implemented in software. The exceptions are numerically intensive operations that are performed frequently, for example, the approximate computation of $|S_M|$ according to equation (9), which also are performed in hardware. The sorting of S_N values to find the test delays that pass the second dwell threshold, and the pausing of PN generator 12, also are done by software.

While the invention has been described with respect to a limited number of embodiments, it will be appreciated that many variations, modifications and other applications of the invention may be made.

WHAT IS CLAIMED IS:

1. A cellular telephony searcher, comprising:
 - (a) a plurality of correlators for correlating a received signal with a pseudonoise sequence;
 - (b) an input mechanism for inputting said pseudonoise sequence into said correlators, each of said correlators receiving said pseudonoise sequence with a different delay; and
 - (c) a delay management mechanism for initializing said delays and subsequently changing said delays, said changing being contingent, for each said correlator, only on an output of said correlator.

2. The searcher of claim 1, wherein each said correlator correlates said received signal with said pseudonoise sequence at said respective delay for a correlation time selected from the group consisting of a first dwell time and a sum of said first dwell time and a second dwell time, said selection being performed separately for each said correlator.

3. The searcher of claim 1, wherein, for each said correlator, said delay management mechanism changes said delay corresponding to said each correlator if an estimated absolute value of said output of said each correlator is less than a threshold common to all said correlators, independent of an estimated absolute value of said output of any other said correlator.

4. The searcher of claim 1, wherein said input mechanism includes:
 - (i) a pseudonoise sequence generator for generating said pseudonoise sequence; and
 - (ii) a delay line for receiving said pseudonoise sequence and outputting a plurality of copies of said pseudonoise sequence, each said copy being outputted with a different said delay.

5. The searcher of claim 4, wherein said delay management mechanism includes:
 - (i) for each said correlator, an index register; and
 - (ii) a multiplexer for directing one of said copies of said pseudonoise sequence to each said correlator in accordance with an index value stored in said index register of said each correlator.

6. In a cellular telephony network including at least one base station and at least one mobile station, each of the at least one mobile station receiving a received signal from the at least one base station, the received signal including a plurality of received values, each said received value having a real part and an imaginary part, a method for each of the at least one mobile station to identify at least one multipath channel to use to communicate with one of the at least one base station, comprising the steps of:
 - (a) generating a pseudonoise sequence;
 - (b) simultaneously performing a plurality of initial correlations of the received signal with said pseudonoise sequence, each of said initial

correlations being performed with a different initial delay of said pseudonoise sequence, said initial correlations being performed for a first dwell time to produce, for each of said initial correlations, an initial first dwell time correlation value; and

- (c) for each said initial correlation:
 - (i) if an estimated absolute value of said initial first dwell time correlation value exceeds a threshold, continuing to perform said each initial correlation,
 - (ii) otherwise, performing a first subsequent correlation of the received signal with said pseudonoise sequence at a first subsequent delay different from any of said initial delays;

wherein, if said performing of at least one of said initial correlations is continued and if at least one of said first subsequent correlations is performed, said continued performing of said at least one initial correlation and said performing of said at least one first subsequent correlation are effected simultaneously.

7. The method of claim 6, wherein, if a plurality of said first subsequent correlations are performed, said first subsequent delays all are mutually different.

8. The method of claim 6, wherein said continued performing of said initial correlations is effected for a second dwell time to produce a second dwell time correlation value.

9. The method of claim 8, wherein said second dwell time is an integral multiple of said first dwell time.

10. The method of claim 6, wherein successive said initial delays differ by a common increment.

11. The method of claim 10, wherein said pseudonoise sequence includes a plurality of chips generated at a certain chip interval, and wherein said common increment is an integral fraction of said chip interval.

12. The method of claim 6, wherein said first subsequent correlations are performed for said first dwell time to produce, for each of said first subsequent correlations, a subsequent first dwell time correlation value, the method further comprising the steps of:

- (d) for each said first subsequent correlation:
 - (i) if an estimated absolute value of said subsequent first dwell time correlation value exceeds a threshold, continuing to perform said each first subsequent correlation;
 - (ii) otherwise, performing a second subsequent correlation of the received signal with said pseudonoise sequence at a second subsequent delay different from any of said initial delays and from any of said first subsequent delays.

13. The method of claim 12, wherein, if said performing of at least one continued correlation, selected from the group consisting of said initial correlations and said first subsequent correlations, is continued, and if at least one of said second subsequent correlations is performed, said continued performing of said at least one continued correlation and said performing of said at least one second subsequent correlation are effected simultaneously.

14. The method of claim 6, further comprising the step of:

- (d) if, after said simultaneous initial correlations are completed up to said first dwell time, all of said delays, whereat said initial correlations are continued and whereat said first subsequent correlations are performed, exceed a shortest initial delay, pausing said generating of said pseudonoise sequence.

15. The method of claim 14, wherein said pausing of said generating of said pseudonoise sequence is effected for a difference between a shortest said delay, whereat said initial correlations are continued and whereat said first subsequent correlations are performed, and said shortest initial delay.

16. The method of claim 6, wherein said correlations are performed using only arithmetical operations selected from the group consisting of additions and subtractions.

17. The method of claim 16, wherein each said correlation is performed as a sum of a plurality of terms, each said term being selected from the group consisting of the real part of a corresponding received value, a negative of the real part of said corresponding received value, the imaginary part of said corresponding received value, and a negative of the imaginary part of said corresponding received value.

18. The method of claim 16, further comprising the step of:

(d) normalizing said correlations.

19. The method of claim 16, wherein each said correlation is performed as a sum of a plurality of terms, each said term being selected from the group consisting of a sum of the real part of a corresponding received value and the imaginary part of said corresponding received value, a negative of said sum of the real part of said corresponding received value and the imaginary part of said corresponding received value, a difference of the real part of said corresponding received value and the imaginary part of said corresponding received value, and a negative of said difference of the real part of said corresponding received value and the imaginary part of said corresponding received value.

20. The method of claim 6, further comprising the step of:

(d) rotating said pseudonoise sequence by 45° prior to performing said correlations.

21. The method of claim 20, further comprising the step of:
- (e) normalizing said correlations.

22. The method of claim 6, wherein said estimated absolute value of said initial first dwell time correlation value is a piecewise linear approximation of an exact absolute value of said initial first dwell time correlation value.

23. The method of claim 22, wherein said piecewise linear approximation is a piecewise linear combination of a larger of an absolute value of a real part of said initial first dwell time and an imaginary part of said initial first dwell time with a smaller of said absolute value of said real part of said initial first dwell time and said absolute value of said imaginary part of said initial first dwell time.

ABSTRACT OF THE DISCLOSURE

A searcher for a mobile station of a cellular telephony network. Pilot signal from nearby base stations are correlated with a pseudonoise sequence inside a search window, using a bank of correlators. Each correlator is assigned a different delay, from among a sequence of delays in the window. At each delay, correlation is performed initially for a first dwell time. If the resulting correlation value exceeds a threshold, the correlation is continued for a second dwell time. Otherwise, the correlator is set to the next delay in the sequence. Only the outputs of second dwell correlations are used to identify the nearest base station. Some correlators may perform first dwell correlations at new delays in the window at the same time that other correlators are still performing second dwell correlations at old delays in the window.




FIG. 1

10




FIG. 2




FIG. 3
(PRIOR ART)

Combined Declaration For Patent Application and Power of Attorney

As a below named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below next to my name;

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled CELLULAR TELEPHONY SEARCHER, the specification of which (check one) ☒ is attached hereto.

☐ was filed on _____ as Application Serial No. _____ and was amended on _____. I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is material to the patentability of this application in accordance with Title 37, Code of Federal Regulations, § 1.56(a).

I hereby claim foreign priority benefits under Title 35, United States Code, § 119 of any foreign application(s) for patent or inventor's certificate listed below and have also identified below any foreign application for patent or inventor's certificate having filing date before that of the application on which priority is claimed:

Prior Foreign Application(s)

Priority Claimed

NONE

(number) (Country) (Day, Month, Year Filed)

☐ Yes ☐ No

(number) (Country) (Day, Month, Year Filed)

☐ Yes ☐ No

(number) (Country) (Day, Month, Year Filed)

☐ Yes ☐ No

I hereby claim the benefit under Title 35, United States Code, § 120 of any United States Application(s) listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States application in the manner provided by the first paragraph of Title 35, United States code, § 112, I acknowledge the duty to disclose material information as defined in Title 37, Code of Federal Regulations, § 1.56(a) which occurred between the filing date of the prior application and the national or PCT international filing date of this application:

NONE

(Application Serial No.) (Filing Date)

Status
(patented, pending, abandoned)

(Application Serial No.) (Filing Date)

Status
(patented, pending, abandoned)

I hereby appoint the following attorneys, with full power of substitution, association, and revocation, to prosecute this application and to transact all business in the Patent and Trademark Office connected therewith.

Mark M. Friedman Registration No. 33,883


Address all Correspondence to:


DR. MARK FRIEDMAN LTD.
c/o ANTHONY CASTORINA
2001 JEFFERSON DAVIS HIGHWAY
SUITE 207
ARLINGTON, VIRGINIA 22202

Direct all telephone calls & faxes to:
ROBERT SHEINBEIN
Phone (703) 415-1581
Fax (703) 415-4864

Continuation of Combined Declaration For Patent Application and Power of Attorney

I hereby further declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statement may jeopardize the validity of the application of any patent issued thereon.

*FULL NAME OF SOLE OR FIRST INVENTOR DOTAN SOKOLOV	INVENTOR'S SIGNATURE x 	DATE x 30/5/99
RESIDENCE SHLONSKY 3A, RAANANA, ISRAEL	CITIZENSHIP ISRAELI	
POST OFFICE ADDRESS SHLONSKY 3A, RAANANA, ISRAEL		

*FULL NAME OF SECOND INVENTOR DAVID BEN-ELI	INVENTOR'S SIGNATURE x 	DATE x 30.5.99
RESIDENCE NAHAL HAYARKON 1, MODIIN, ISRAEL	CITIZENSHIP ISRAELI	
POST OFFICE ADDRESS NAHAL HAYARKON 1, MODIIN, ISRAEL		

*FULL NAME OF THIRD INVENTOR	INVENTOR'S SIGNATURE	DATE
RESIDENCE	CITIZENSHIP ISRAELI	
POST OFFICE ADDRESS		

*FULL NAME OF FOURTH INVENTOR	INVENTOR'S SIGNATURE	DATE
RESIDENCE	CITIZENSHIP ISRAELI	
POST OFFICE ADDRESS		

*FULL NAME OF FIFTH INVENTOR	INVENTOR'S SIGNATURE	DATE
RESIDENCE	CITIZENSHIP ISRAELI	
POST OFFICE ADDRESS		

*FULL NAME OF SIXTH INVENTOR	INVENTOR'S SIGNATURE	DATE
RESIDENCE	CITIZENSHIP ISRAELI	
POST OFFICE ADDRESS		